

Under load RPM table

Torqstar 7025 7040 7050

Specified rpms can vary due to the production process about +/- 4%
 The mechanical rpm limit is max. 20000 rpm
 rpms are determined with 15° timing

windings	7015	7025	7040	7050
	rpm per volt (under load)			
4	1148	689	430	344
5	918	551	344	275
6	765	459	287	230
7	655	394	246	196
8	574	344	215	173
9	510	306	191	153
10	459	275	173	138
11	417	251	156	125
12	383	230	144	115
13	353	212	133	106
14	328	196	123	99
15	306	184	115	92
16	287	173	108	86
17	270	162	101	81
18	255	153	96	77
19	241	145	91	72
20	230	138	86	69
21	218	131	82	65
22	208	125	78	63
23	200	120	75	60
24	191	134	71	58
25	184	111	69	55
26	177	106	66	53
27	170	102	64	51
28	164	99	61	49
29	158	95	60	48
30	153	92	58	46
31	148	89	55	44
32	144	86	54	43
33	139	83	52	42
34	135	81	51	41
35	131	79	49	39
36	128	77	48	38
37	124	75	47	37
38	121	72	45	36
39	117	71	44	35
40	115	69	43	34